



Features and Benefits

- 2 or 3 Position switches
- 2 keys supplied
- Key removable in all positions

Technical Overview

The EP-FS are a range of safety switches for use in the event of fire or other emergency.

Usually they are located at exits to gas plant rooms. Units are key operated with a 2 or 3-position switches. The key is removable in all switch positions.

Product Codes

EP-FS-1	2-Position red fireman's switch
EP-FS-2	3-Position red fireman's switch

Specification

Switch rating	2A @ 250Vac
Dimensions	86 x 86 x 50mm
Keys	2 supplied (removable in all positions)
Connections	4x 100mm flying leads
Installation category	IEC 664 Category II
Pollution degree	IEC 664 degree 1
Operating range	-20 to +55°C
Country of origin	UK
Conformity	LVD, CE & UKCA Marked

WEEE Directive:



At the end of the products useful life please dispose as per the local regulations. Do not dispose of with normal household waste. Do not burn.



Installation

1. The EP-FS range should only be installed by a competent, suitably trained technician, experienced in installation with hazardous voltages. (>50Vac & <1000Vac or >75Vdc & 1500Vdc)
2. Ensure that all power is disconnected before carrying out any work on the EP-FS range.
3. Separate the cover from the housing base.
4. Mount the housing base as required, if flush mounting a minimum box depth of 35mm is recommended.
5. Terminate the cores leaving some slack inside the unit.
6. Replace the front cover.

Switch Positions

EP-FS-1:

Switch position	"0"	Switch position	"1"
Red - Yellow	Closed	Yellow - Blue	Closed

EP-FS-2:

Switch position	"Auto"	Switch position "Off"	Switch position "Extract"
Blue - Yellow	Closed	Yellow - Black	Closed
			Black - Red
			Closed

Whilst every effort has been made to ensure the accuracy of this specification, Sontay cannot accept responsibility for damage, injury, loss or expense from errors or omissions. In the interest of technical improvement, this specification may be altered without notice.